

# D284 Ultraviolet Flame Detector

www.boschsecurity.com



**BOSCH**

Invented for life



- ▶ Highly reliable, long-lasting ultraviolet (UV) receptor tube
- ▶ Low power consumption
- ▶ Can be mixed with other detector types on the control panel's initiation detection circuit (IDC)
- ▶ Easily maintained; can be cleaned without disassembly

Use the D284 wherever fires can develop quickly. Suitable applications are:

- Petroleum storage areas
- Photographic or film storage areas
- Computer rooms
- Print shops
- Museums



**Notice**

The D284 is not a substitute for smoke or heat detectors. It provides an added level of notification for fast flaming fires only.



**Notice**

This product is not UL Listed.

## Functions

### Basic Operation

An ultraviolet-detector tube within the D284 absorbs very weak ultraviolet (UV) light such as that emitted from a flame and produces an electrical current. The detector's electronic circuitry translates this current into an alarm signal. A counter-current prevents alarm

signals from single-pulse UV sources such as lightning or cosmic flares. Additionally, the circuit is tuned to respond only to wavelengths from 185 nm to 300 nm.

### Coverage Area

The D284's response depends on both the size of the fire and the distance from the fire to the detector; therefore the effective coverage area varies. Very small fires must have a duration of at least 7 sec if within 12 ft (3.7 m) of the detector and a duration of 30 sec if within 12 ft to 25 ft (3.7 m to 7.6 m) of the detector.

## Installation/configuration notes

### Compatibility Information

The D284 is compatible with the following products:

Category	Product ID	Product Description
Control Panels:	All Bosch Security Systems 24 V fire alarm control panels	
Detector Bases:	D250A <sup>1</sup>	Two-wire detector base (12/24 VDC)
	D253	Two-wire detector base (24 VDC)
	D261AW <sup>1</sup>	Two-wire detector base (12/24 VDC)
	D261W <sup>1</sup>	Two-wire detector base (12/24 VDC)

D271W <sup>1</sup>	Four-wire detector base (12/24 VDC)
D280A	Two-wire detector base (24 VDC)
D290	Four-wire detector base (24 VDC)

<sup>1</sup> All 12 VDC or 24 VDC bases must be set for 24 VDC operation.

## Parts included

Quant.	Component
1	Flame detector

## Technical specifications

### Environmental Considerations

Relative Humidity:	up to 95%, non-condensing at +104°F (+40°C)
Temperature (operating):	+14°F to +122°F (-10°C to +50°C)

### Mechanical Properties

Color:	Ivory
Dimensions (diameter x H)	4 in. x 2 in. (10.2 cm x 5.1 cm)
Material:	ACS plastic (acrylonitrile-chlorinated PE-styrene)

### Output

Contact Rating:	260 mA at 24 VDC
-----------------	------------------

### Power Requirements

#### Current

Alarm:	0.25 mA at 24 VDC
Standby:	0.2 mA at 24 VDC

#### Voltage (operating)

Nominal:	24 VDC
Range:	17.6 VDC to 27.7 VDC

### Response

Detection Angle:	120° conical
UV Sensitivity:	185 nm to 300 nm

## Ordering information

### D284 Ultraviolet Flame Detector

The D284 is an ultraviolet light flame detector that provides an added level of notification for fast flaming fires only. It is not a substitute for smoke or heat detectors and is not UL Listed.

Order number **D284**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com