

D8128D OctoPOPIT Eight-point Expander

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Provides point identification for initiating devices
- ▶ Expands the number of points in the system
- ▶ DIP switch programmable

The D8128D OctoPOPIT module combines the functions of the D8125 POPEX module and the D8127 and D9127U and D9127T POPIT modules to provide eight Class B (Style B) off-board points in a single module. The D8128D OctoPOPIT and D8125 POPEX modules can be wired in parallel to the ZONEX Bus terminals on the same panel.

System overview

The module can be installed inside the enclosure of the control panel, or the module can be installed in a separate enclosure and connected to the control panel.

Functions

Address Switches

There is a set of DIP switches for setting point assignments and line termination. Switches 1 to 4 assign the sensor loops to point numbers on a compatible control panel. Switch 5 sets the line termination.

Point DIP Switches

Activate or deactivate each point connected to the module by placing its respective DIP switch in the closed or open position. The point DIP switch can be used to deactivate conflicting points.

Certifications and approvals

Australia C-Tick

Region	Certification
USA	<p>UL</p> <p>AMCX: Central Station Alarm Units (UL1610, UL1635), AOTX: Local Alarm Units (UL464, UL609), AOTX7: Local Alarm Units Certified for Canada (cULus), APOU: Proprietary Alarm Units (UL1076), NBSX: Household Burglar Alarm System Units (UL1023), NBSX7: Household Burglar Alarm System Units Certified for Canada (cULus), UOXX: Control Unit Accessories, System (UL864, 9th edition), UTOU: Control Units and Accessories - Household System Type (UL985), UTOU7: Control Units and Accessories - Household System Type Certified for Canada (cULus)</p>
	<p>NYC-MEA</p> <p>12-92-E, Vol. 12 12-92-E, Vol. 12</p>
	<p>NYC-MEA</p> <p>12-92-E, Vol. 15 12-92-E, Vol. 15</p>
	<p>FDNY-CoA</p> <p>6059</p>
	<p>CSFM</p> <p>7167-1615:0100 CONTROL UNIT (HOUSEHOLD)</p>

Region	Certification	
	CSFM	7165-1615:0113 FIRE ALARM CONTROL UNIT (COMMERCIAL)
	CSFM	7167-1615:0243
	CSFM	7165-1615:0242
	CSFM	7165-1615:0119
	CSFM	7167-1615:0239
	CSFM	7165-1615:0238

Installation/configuration notes

Compatibility Information

Control Panels

All G Series control panels, D9412, D7412, and D7212



Notice

The D7212GV3, D7212GV2, D7212G, and D7212 are not listed for commercial fire applications.

Connection Considerations

If the module is installed in a separate enclosure, it can be placed up to 60 m (200 ft) from the control panel:

Maximum Wire Impedance: 4 Ω

Distance (maximum)	Wire Size
60 m	0.6 mm
60 m	1.0 mm
200 ft	22 AWG
200 ft	18 AWG

The module can be wired to the control panel using the module's terminal strip or using Molex connectors. The Molex connectors are useful when multiple D8128D modules are in use. The terminal strip is easier to use in cases when the module is connected directly to the control panel.

Parts included

Quantity	Component
1	OctoPOPIT
1	Hardware pack
1	Literature pack

Technical specifications

Environmental Considerations

Temperature (Operating):	0°C to +49°C (+32°F to +120°F)
--------------------------	--------------------------------

Loop

Wire Resistance:	100 Ω maximum
Response Time:	1 second (supervised with a 1 kΩ end-of-line resistor)

Power Requirements

Current (alarm):	50 mA maximum
Current (standby):	25 mA maximum
Voltage:	12 VDC nominal

Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

Molex is a registered trademark of Molex Incorporated

Ordering information

D8128D OctoPOPIT Eight-point Expander

Provides 8 off-board points and a set of DIP switches. Order number **D8128D**

D137 Mounting Bracket

Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.

Order number **D137**

D8103 Enclosure

Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).

Order number **D8103**

D8108A Attack Resistant Enclosure

Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. Requires the D2402 Mounting Plate.

Order number **D8108A**

D8109 Fire Enclosure

Red steel enclosure measuring 40.6 cm x 40.6 cm x 8.9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes a lock and key set.

Order number **D8109**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com