RC-10 Remote controller

RC-10 wireless remote control is designed to work with control panels CPX2xxNWB and transmitters which have a radio receiver. This device allows convenient and easy operation of the system thanks to four buttons, which can be programmed with one of several functions available.




Specification	
Transmission frequency	433,92 MHz
Transmission distance	up to 300m
in open air	
Communication	one way
Current during	8 mA
transmission	
Standby current	0,01µA
Batteries	2x lithium 3V CR2016
Battery lifetime	about 3 years
Operating temperature	-10 to +50°C
Dimensions	60 x 33 x 10,5 mm
Total weight	20,5 g

Batteries change

To change the batteries, open the remote's cover, making use of a notch on the side where two halves of the remote meet. Then, slide out used batteries, and insert a new ones with the "+" side facing upward, making sure that it is entirely fitted into the batteries holder. The following figure shows the correct way to install the batteries.

2x CR2016



MANUFACTURER

EBS Sp. z o.o. 59 Bronislawa Czecha St. 04-555 Warsaw, POLAND Tech. support:+48 22 51 88 477 E-mail: support@ebs.pl Webpage : www.ebs.pl

